

Cryptanalysis of a computer cryptography scheme based on a filter bank

David Arroyo ^{a,*}, Chengqing Li ^b, Shujun Li ^c and
Gonzalo Alvarez ^a

^a*Instituto de Física Aplicada, Consejo Superior de Investigaciones Científicas,
Serrano 144, 28006 Madrid, Spain*

^b*Department of Electronic Engineering, City University of Hong Kong, 83 Tat
Chee Avenue, Kowloon Tong, Hong Kong SAR, China*

^c*FernUniversität in Hagen, Lehrgebiet Informationstechnik, Universitätsstraße 27,
58084 Hagen, Germany*

Abstract

This paper analyzes the security of a recently-proposed signal encryption scheme based on a filter bank. A very critical weakness of this new signal encryption procedure is exploited in order to successfully recover the associated secret key.

Key words: Chaotic encryption, logistic map, known-plaintext attack, cryptanalysis

PACS: 05.45.Ac, 47.20.Ky.

1 Introduction

The application of chaotic systems to cryptographical issues has been a very important research topic since the 1990s [1–4]. This interest was motivated by the close similarities between some properties of chaotic systems and some characteristics of well-designed cryptosystems [5, Table 1]. Nevertheless, there exist security defects in some chaos-based cryptosystems such that they can be partially or totally broken [6–11].

In [12] the encryption procedure is carried out by decomposing the input plaintext signal into two different subbands and masking each of them with

* Corresponding author: David Arroyo (david.arroyo@iec.csic.es).

a pseudo-random number sequence generated by iterating the chaotic logistic map. The decomposition of the input plaintext signal $x[n]$ is driven by

$$t_0[n] = K_0 \sum_{\forall m} x[m] h_0[2n - m], \quad (1)$$

$$t_1[n] = K_1 \sum_{\forall m} x[m] h_1[2n - m], \quad (2)$$

where h_0, h_1 are so-called “analysis filters” and K_0, K_1 are gain factors.

Then, the masking stage generates the ciphertext signal $(v_0[n], v_1[n])$ according to the following equations:

$$v_0[n] = t_0[n] + \alpha_0(t_1[n]), \quad (3)$$

$$v_1[n] = t_1[n] - \alpha_1(v_0[n]), \quad (4)$$

where $\alpha_i(u) = u + s_i[n]$ and $s_i[n]$ is the state variable of a logistic map with control parameter $\lambda_i \in (3, 4)$ defined as follows¹

$$s_i[n] = \lambda_i s_i[n-1](1 - s_i[n-1]). \quad (5)$$

Substituting $\alpha_i(u) = u + s_i[n]$ into Eqs. (3) and (4), we have

$$v_0[n] = (t_0[n] + t_1[n]) + s_0[n], \quad (6)$$

$$v_1[n] = (t_1[n] - v_0[n]) - s_1[n]. \quad (7)$$

The secret key of the cryptosystem is composed of the initial conditions and the control parameters of the two logistic maps involved, i.e., $s_0[0], s_1[0], \lambda_0$ and λ_1 .

The decryption procedure is carried out by doing

$$t_1[n] = v_1[n] + \alpha_1(v_0[n]), \quad (8)$$

$$t_0[n] = v_0[n] - \alpha_0(t_1[n]). \quad (9)$$

Then, the plaintext signal is recovered with the following filtering operations:

$$\tilde{x}[n] = \frac{1}{K_0} \sum_{\forall m} t_0[m] f_0[n - 2m] + \frac{1}{K_1} \sum_{\forall m} t_1[m] f_1[n - 2m], \quad (10)$$

¹ In [12], the authors use x_i to denote the state variable of the logistic map. However, this nomenclature may cause confusion because the plaintext signal is denoted by x . Therefore, we turn to use another letter, s . In addition, we unify the representation of $x_i(k)$ to be in the form $s_i[n]$ because all other signals are in the latter form.




Fig. 1. Bifurcation diagram of the logistic map

where f_0, f_1 are so-called “synthesis filters”. To ensure the correct recovery of the plaintext signal, the analysis and synthesis filters must satisfy a certain requirement as shown in Eq. (8) of [12]. The reader is referred to [12] for more information about the inner working of the cryptosystem.

This paper focuses on the security analysis of the above cryptosystem. The next section points out a security problem about the reduction of the key space. Section 3 discusses how to recover the secret key of the cryptosystem by a known-plaintext attack. In the last section the conclusion is given.

2 Reduction of the key space

As it is pointed out in [5, Rule 5], the key related to a chaotic cryptosystem should avoid non-chaotic areas. In [12] it is claimed that the key space of the cryptosystem under study is given by the set of values λ_i and $s_i[0]$ satisfying $3 < \lambda_i < 4$ and $0 < s_i[0] < 1$ for $i = 0, 1$. However, when looking at the bifurcation diagram of the logistic map (Fig. 1), it is obvious that not all candidate values of λ_i and $s_i[0]$ are valid to ensure the chaoticity of the logistic map. There are periodic windows which have to be avoided by carefully choosing λ_i . As a consequence, the available key space is drastically reduced.

3 Known-plaintext attack

In a known-plaintext attack the cryptanalyst possesses a plaintext signal $\{x[n]\}$ and its corresponding encrypted subband signals $\{v_0[n]\}$ and $\{v_1[n]\}$. Because $\{h_0[n]\}$, $\{h_1[n]\}$, K_0 and K_1 are public, we can get $\{t_0[n]\}$ and $\{t_1[n]\}$ from $\{x[n]\}$. Then we can get the values of $\{s_0[n]\}$ and $\{s_1[n]\}$ as follows:

$$s_0[n] = v_0[n] - t_0[n] - t_1[n], \quad (11)$$

$$s_1[n] = t_1[n] - v_0[n] - v_1[n]. \quad (12)$$

For $n = 0$, the values of the subkeys $s_0[0]$ and $s_1[0]$ have been obtained. Furthermore, we can obtain the control parameters by just doing the following operations for $i = 0, 1$:

$$\lambda_i = \frac{s_i[n+1]}{s_i[n](1 - s_i[n])}. \quad (13)$$

In [12], the authors did not give any discussion about the finite precision about the implementation of the cryptosystem in computers. If the floating-point precision is used, then the value of λ_i can be estimated very accurately. It was experimentally verified that the error for the estimation of λ_i using (13), and working with floating-point precision, was never greater than $4 \cdot 10^{-12}$. If the fixed-point precision is adopted, the deviation of the parameter λ_i estimated exploiting Eq. (13) from the real λ_i may be very large. Fortunately, according to the following Proposition 1 [13, Proposition 2], the error is limited to $2^4/2^L$ (which means only 2^4 possible candidate values to be further guessed) when $s[n+1] \geq 0.5$.

Proposition 1 *Assume that the logistic map $s[n+1] = \lambda \cdot s[n] \cdot (1 - s[n])$ is iterated with L -bit fixed-point arithmetic and that $s[n+1] \geq 2^{-i}$, where $1 \leq i \leq L$. Then, the following inequality holds: $|\lambda - \tilde{\lambda}| \leq 2^{i+3}/2^L$, where $\tilde{\lambda} = \frac{s[n+1]}{s[n] \cdot (1 - s[n])}$.*

4 Conclusion

In this paper we have analyzed the security properties of the cryptosystem proposed in [12]. It has been shown that there exists a great number of weak keys derived from the fact that the logistic map is not always chaotic. In addition, the cryptosystem is very weak against a known-plaintext attack in the sense that the secret key can be totally recovered using a very short plaintext.

Consequently, the cryptosystem introduced by [12] should be discarded as a secure way of exchanging information.

Acknowledgments

The work described in this paper was partially supported by Ministerio de Educación y Ciencia of Spain, Research Grant SEG2004-02418. Shujun Li was supported by the Alexander von Humboldt Foundation, Germany.

References

- [1] S. Li, Analyses and new designs of digital chaotic ciphers, Ph.D. thesis, School of Electronic and Information Engineering, Xi'an Jiaotong University, Xi'an, China, available online at <http://www.hooklee.com/pub.html> (June 2003).
- [2] G. Alvarez, F. Montoya, M. Romera, G. Pastor, Chaotic cryptosystems, in: L. D. Sanson (Ed.), Proc. 33rd Annual 1999 International Carnahan Conference on Security Technology, IEEE, 1999, pp. 332–338.
- [3] L. Kocarev, Chaos-based cryptography: A brief overview, IEEE Circuits Syst. Mag. 1 (2001) 6–21.
- [4] T. Yang, A survey of chaotic secure communication systems, Int. J. Comp. Cognition 2 (2) (2004) 81–130.
- [5] G. Alvarez, S. Li, Some basic cryptographic requirements for chaos-based cryptosystems, International Journal of Bifurcation and Chaos 16 (8) (2006) 2129–2151.
- [6] G. Alvarez, F. Montoya, M. Romera, G. Pastor, Cryptanalyzing a discrete-time chaos synchronization secure communication system, Chaos, Solitons and Fractals 21 (3) (2004) 689–694.
- [7] G. Alvarez, F. Montoya, M. Romera, G. Pastor, Breaking parameter modulated chaotic secure communication system, Chaos, Solitons and Fractals 21 (4) (2004) 783–787.
- [8] G. Alvarez, F. Montoya, M. Romera, G. Pastor, Cryptanalyzing an improved security modulated chaotic encryption scheme using ciphertext absolute value, Chaos, Solitons and Fractals 23 (5) (2004) 1749–1756.
- [9] G. Alvarez, S. Li, F. Montoya, G. Pastor, M. Romera, Breaking projective chaos synchronization secure communication using filtering and generalized synchronization, Chaos, Solitons and Fractals 24 (3) (2005) 775–783.

- [10] S. Li, G. Alvarez, G. Chen, Breaking a chaos-based secure communication scheme designed by an improved modulation method, *Chaos, Solitons and Fractals* 25 (1) (2005) 109–120.
- [11] G. Alvarez, Security problems with a chaos-based deniable authentication scheme, *Chaos, Solitons and Fractals* 26 (1) (2005) 7–11.
- [12] B. W.-K. Ling, C. Y.-F. Ho, P. K.-S. Tam, Chaotic filter bank for computer cryptography, *Chaos, Solitons and Fractals* 34 (2007) 817–824.
- [13] S. Li, C. Li, G. Chen, K.-T. Lo, Cryptanalysis of the RCES/RSES image encryption scheme, *J. Systems and Software*, in press, doi:10.1016/j.jss.2007.07.037 (2007).